



















RF Broadband bi directional coupler *

Model	Freq.min (MHz)	Freq.max (MHz)	Power (W)	Coupling	Gain var. (+/- dB)	Directivity (dB)	Insertion loss (dB)	Case
RFC001250-40-100 	0,01	250	100	40	1	> 20	< 0,3	BO13-1 
RFC001250-40-250 	0,01	250	250	40	1	> 20	< 0,3	BO13-1 
RFC001250-40-600 	0,01	250	600	40	1	> 20	< 0,3	BO03-08 
RFC001250-50-1000	0,01	250	1000	50	1	> 20	< 0,3	
RFC001400-40-100 	0,01	400	100	40	1	> 15	< 0,3	BO13-1 
RFC001400-40-250 	0,01	400	250	40	1	> 15	< 0,3	BO13-1 
RFC001400-40-600 	0,01	400	400	40	1	> 15	< 0,3	BO03-08 
RFC9002000-40-150 	900	2000	150	40	1	> 15	< 0,3	BO28 
RFC801000-40-150 	80	1000	150	40	1	> 20	< 0,2	BO28 
RFC801000-40-250 	80	1000	250	40	1	> 20	< 0,2	BO28 

* including power detector upon request