

# RF Power Amplifier module

## AP20002400-4-COFDM

This solid state power amplifier is designed for reliable, trouble-free service. It operates in a **class A** so as a 12 V DC power supply. The amplifier is accommodated in aluminium housing.

### Features :

- \* 35 Watts saturated CW output power
- \* 40 dB minimum gain
- \* RF power indicator
- \* Electronic Attenuator with preset power
- \* Overvoltage and reverse protection
- \* Isolator included

### Applications :

- \* RF links digital TV
- \* Fields Test

### Specifications

Characteristics	Data	Units
Frequency range	2000 MHz - 2400 MHz	MHz
RF output power - 27 dBc shoulder		
Typ.	5	W
Min	4	W
Class	A	
Power gain	40	dB
Flatness	+/- 2 dB	dB
Input power for rated output power	-3	dBm
Max. input power	10	dBm
In / Out impedances nom.	50	Ohms
Input VSWR	2 : 1	
Variable gain	over 15 dB	
VSWR mismatch	Infinite @ 4 W COFDM	
Protection circuits	Load VSWR, over temperature	
Harmonics typ.	-20	dBc
Spurious typ.	-60	dBc
Modulation capability	100	%
Noise Figure typ.	10	dB
Intercept point 3 rd Order typ.		dBm
RF connectors	N female	
Cooling	forced air (have to be added)	
Operating temperature Range	0 °C ... + 45	° C
Power Supply	11,5 V to 15 V DC I 10 A	V
Dimensions (W x L x H)	245 x 200 x 80	mm
All data at room temperature + 22 °C, into 50 Ohms, subject to change without notice		

Made in European Union

14/03/2002

[WWW.RFPA.com](http://WWW.RFPA.com)

**R.F.P.A. S.A.**

Parc d'activité de Fontaudin F33370 Artigues près Bordeaux

France Tél : +33 (0)5 56 86 85 84 Fax: + 33 (0) 5 56 86 55 56